



ST6003 - Stereo Tuner

The ST6003 is an FM/MW Stereo analogue tuner with access to all major frequencies and has a high-sensitivity front end to ensure drift-free reception. The RDS tuner lets you tune by frequency or program type, while the new full dot matrix display clearly indicates the frequencies and radio data such as station name or radio text. It comes with 50 station presets and a sleep timer function. And, via the Marantz D-Bus you can remote control the ST6003 with any Marantz amplifier remote or optional RC101. In total, the ST6003 combines high-quality audio components for the best sound with functionality and ease of use.

MAIN FEATURES

- Drift-free stereo FA/AM reception
- RDS function
- Full dot matrix display
- Customised components
- Frequency direct input
- 50 presets
- Marantz D-bus

because music matters



SPECIFICATIONS	ST6003
DAB/DAB+/DMB-A/FM/MW	-/-/0/o
High grade audio components	o
Presets	50 (FM/AM)
Auto tuning	o
RDS: PTY/PS/RT	o/o/o
Sleep / timer	o/-
Display dimmer (via dimmer)	o
TRiple IR-code	o
IN/OUTPUTS	-
Analogue Out	1
DAB terminal (1F)	-
FM Antenna	1
AM Antenna	1
Digital outputs: Coaxial/optical	-/-
Ethernet	-
D-bus	o
RS-232C	-
SPECIFICATIONS	
TUNER SECTION FM	
Frequency range	87.5-108 MHz
Signal to Noise Ratio (Mono/Stereo)	75dB/70dB
Total Harmonic Distortion (Mono/Stereo)	0.2% / 0.3%
Frequency Response	50Hz - 15kHz (+0.5 / -3dB)
Channel Selectivity (FM)	60dB
Usable Sensitivity	IHF 1.8 uV/16.4 dBf
Stereo separation	1 kHz, 45dB (stereo)
TUNER SECTION AM	-
Frequency Range: MW/LW	531-1602kHz/-
Signal to Noise Ratio: MW/LW	50dB/-
GENERAL	
Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/o
Metal Front Panel	o
Remote Control	via D-bus
Power Consumption in W	9
Standby Power Consumption in W	0.4
Detachable Power Cable	o
Maximum Dimensions in mm	440x341x104,5
Weight in kg	4.1